

**STEP 3: FA0G**

Press MODE button into this window---COLOR FADE SELECTION:

**FA00** RGB: 00-99 speed adjustable.

**FF00** STROBE: 00-99 speed adjustable.

**STEP4: SU00**

Sound active function, sensitivity can be adjusted from 00-99.

**STEP5: AUTO**

Auto run effect.

**STEP 6: SLAV**

Press MODE button into this window---SLAVE SETTING.

**STEP 7: A001**

Press MODE button into this window---DMX ADDRESS SETTING.

Connect with the standard DMX controller to fulfill the following operation and function:

**DMX channel assignment and function:**

**2channel mode:**

CH1	CH2
Master Dimmer (0-240)	0-4: Blackout
Strobe (241-255)	5-80: Color Micro
	81-150: Color Jump
	151-255: Color Fade

**3channel mode:**

CH1	CH2	CH3
RED (0-255)	Green (0-255)	Blue (0-255)

**4channel mode:**

CH1	CH2	CH3	CH4
RED (0-255)	Green (0-255)	Blue (0-255)	Amber (0-255)

**7channel mode:**

CH1	CH2	CH3	CH4	CH5	CH6	CH7
Dimmer (0-255)	Strobe (0-255)	RED (0-255)	GREEN (0-255)	BLUE (0-255)	Amber (0-255)	0-4: Blackout
						5-80: Color Micro
						81-150: Color Jump
						151-255: Color Fade

## SLIM SPOT USER MANUAL

Thanks for choosing the LED SLIM SPOT light. This is the innovative LED application for professional lightings. Since the RGBA four colors ultra bright LED lamps, the unit can combine more than billions of color effects. Thanks to the waterproof and heat sink structure without any noisy, this item can be used for the buildings, studio center, theatre, entertainment stage, dancing halls, clubs etc..

### **Technical Specifications:**

- LED: 229 RGBA 10mm (R36, B63, G61, A69)  
Beam angle: 25 degree
- Power: 50W
- Voltage: AC100V-240V, 60Hz-50Hz
- Built-in scenes
- DMX control: 2ch/3ch/4ch/7ch
- Master and slave control
- Size: 23\*23\*7.6CM
- Weight: 1.8kgs

### **Operation Instructions (LED DISPLAY):**

On LED Display, please NOTE:

**When the digit flash, that means you can select this mode and via UP/DOWN to choose. After making your choice, press SET UP for confirmation of your setting everytime!!**

#### **STEP 1: C000**

Press MODE button into this window---STATIC COLOR SELECTION.

C100 RED: 00-99 beam level adjustable.

C200 GREEN: 00-99 beam level adjustable.

C300 BLUE: 00-99 beam level adjustable.

C400 AMBER: 00-99 beam level adjustable

CF00 STROBE:00-99 speed adjustable.

#### **STEP 2: JU00**

Press MODE button into this window---COLOR JUMP SELECTION.

JU00 RGBA 15 colors: 00-99 speed adjustable.

JF00 STROBE: 00-99 speed adjustable.