

## DMX Values

### 6 channels mode

CH	Value	Function
1	0-255	Red
2	0-255	Green
3	0-255	Blue
4	0-255	Amber
5	0-255	White
6	0-255	UV

### 10 channels mode

CH	Value	Function
1	0-255	Master Dimmer RGBAW+UV
2	0-255	Red
3	0-255	Green
4	0-255	Blue
5	0-255	Amber
6	0-255	White
7	0-255	UV
8	0-255	Strobe (Speed Adjustment)
9	0-50	No function
	51-100	Colors Output
	101-150	Colors Jump Changing
	151-200	Colors Growing/Fading
	201-250	Colors Pulse Change
	251-255	Sound Active
10	0-255	Speed for Macro Function