

DMX Values

3 channels mode

CH	Value	Function
1	0-255	Hue
2	0-255	Saturation
3	0-255	Value

6 channels mode

CH	Value	Function
1	0-255	Red
2	0-255	Green
3	0-255	Blue
4	0-255	Amber
5	0-255	White
6	0-255	UV

8 channels mode

CH	Value	Function
1	0-255	Master Dimmer
2	0-255	Red
3	0-255	Green
4	0-255	Blue
5	0-255	Amber
6	0-255	White
7	0-255	UV
8	0-255	Strobe

DMX Values

11 channels mode

CH	Value	Function
1	0-255	Master Dimmer
2	0-255	Red
3	0-255	Green
4	0-255	Blue
5	0-255	Amber
6	0-255	White
7	0-255	UV
8	0-255	Strobe
9	0-15	None
	16-95	Auto Mode
	96-175	Fade Mode
	176-255	Sound Active
10	0-255	Dimmer Speed
11	0-5	Default Dimmer
	6-65	Linear Dimmer Mode
	66-125	Curve Dimmer Mode
	126-185	Theatre Dimmer Mode
	186-255	Studio Dimmer Mode