

DMX Values

3 channels mode

CH	Value	Function
1	0-10	Spark Off
	11-255	Spark On
2	0-149	No Effect
	150-255	Clear Material (Blower only, no heat) Recommended after each use.
3	0-199	Heating on (Ch 1 functions will not work)
	200-255	Stop heating (Ch1 functions will not work) *NOTE: The “Stop heating” function can be useful when a machine needs to be part of a live event setting for an extended time while remaining cool.