

## DMX Values

### 8 channels mode

CH	Value	Function	
1	0-10	No Function	Macro Functions
	11-50	Macro A1	
	51-100	Macro A2	
	101-150	Macro A3	
	151-200	Macro A4	
	201-255	Macro A5	
2	0-39	All Color	Color Selections
	40-49	Red	
	50-59	Green	
	60-69	Blue	
	70-79	Yellow	
	80-89	Cyan	
	90-99	Purple	
	100-109	Motor Running	
	110-119	Red + Green	
	120-129	Red + Blue	
	130-139	Red + Motor Running	
	140-149	Green + Blue	
	150-159	Green + Motor Running	
	160-169	Blue + Motor Running	
	170-179	Red + Green + Motor	
	180-189	Red + Blue + Motor	
190-199	Green + Blue + Motor		
200-209	Red + Green + Blue		
210-255	Red + Green + Blue + Motor		

## DMX Values

### 8 channels mode

CH	Value	Function
3	0-255	Adjust Speed
4	0-255	Adjust Master Dimming
5	0-255	Adjust Red
6	0-255	Adjust Green
7	0-255	Adjust Blue
8	0-255	R + G + B + Motor