



**ColorKey**  
creative lighting

# Twin Airship

CKU01-1050



**USER MANUAL**

---

# Introduction

Thank you for purchasing the ColorKey Twin Airship. Please read these instructions carefully before use. Operating this fixture according to these instructions is important to avoid any possible damage or accidents caused by misuse.

## ➤ Packing list

- 1x Twin Airship unit
- 1x Power cord
- User Manual

## Safety

**Caution!** Opening this unit voids warranty. Contact ColorKey for any service requests.

**Warning!** To avoid electrical shock, be sure to disconnect power before any service or when moving or setting up the fixture.

**Caution!** Avoid direct eye exposure with the fixture when on.

- This fixture is for indoor use only.
- This fixture must be installed a minimum distance of 5 meters (16'4") away from any lighted objects.
- Do not install or operate this fixture near flammable materials.
- This device must be installed, operated, and maintained by a qualified professional.
- Do not touch the fixture with bare hands during operation as the surface temperature of the fixture can exceed 60°C (140°F). Turn off power and wait 15 minutes for the fixture to cool before attempting to touch it.
- Please check if the voltage is in accordance with the rated power before installing.
- Do not operate this fixture if the power cord has been damaged. Turn off fixture and replace with a power cord of similar rating.

---

# Technical Information

Power supply: 90V/240V; 60/50Hz

Light source: 128 LED's (R8/G56/B40/W24)

Power consumption: 20W

Control: Sound active; Auto


Working temperature: Indoor -20°C to 40°C

Protection rating: IP20

**Notice to consumer:** ColorKey offers a 1-year limited warranty. Please visit our website at [www.ColorKeyLED.com](http://www.ColorKeyLED.com) to register your product.

**Please note:** As we continue to work towards improving our products and your experience as a user, we recommend that you check our website periodically for updates to user manuals and specifications at [www.ColorKeyLED.com](http://www.ColorKeyLED.com) or you may contact us directly at [info@colorkeyled.com](mailto:info@colorkeyled.com).

# Dip Switch Settings

Mode	Function	Address (DIP)
Auto 1	<p>Slower</p>  <p>Faster</p>	1-10 (OFF)
Auto 2		8 (ON)
Auto 3		8+7 (ON)
Auto 4		8+7+6 (ON)
Auto 5		8+7+6+5 (ON)
Auto 6		8+7+6+5+4 (ON)
Auto 7		8+7+6+5+4+3 (ON)
Auto 8		8+7+6+5+4+3+2 (ON)
Sound 1	Speed controlled by sound	9 (ON)
Sound 2	Sound active off light	9+10 (ON)