

DMX Values

6 channels mode

CH	Value	Function
1	0-255	Red
2	0-255	Green
3	0-255	Blue
4	0-255	Amber
5	0-255	White
6	0-255	UV

10 channels mode

CH	Value	Function
1	0-255	Master Dimmer
2	0-255	Red
3	0-255	Green
4	0-255	Blue
5	0-255	Amber
6	0-255	White
7	0-255	UV
8	0-255	Strobe
9	0-2	No function
	3-127	Color1-Color32
	128-191	Color Macro 1-16
	192-255	Color Fade 1-16
10	0-255	Speed (Color Macro and Fade) (Slow to Fast)